

TFT COLOR LCD MODULE

NL128102BC29-10

48.0cm (19.0 Type)

SXGA

LVDS Interface (2 ports)

PRELIMINARY DATA SHEET

DOD-PP-0492 (2nd edition) 



**This PRELIMINARY DATA SHEET is updated
document from DOD-PP-0486(1)**

**All information is subject to change without notice.
Please confirm the sales representative before
starting to design your system.**

INTRODUCTION

The Copyright to this document belongs to NEC LCD Technologies, Ltd. (hereinafter called "NEC"). No part of this document will be used, reproduced or copied without prior written consent of NEC.

NEC does and will not assume any liability for infringement of patents, copyrights or other intellectual property rights of any third party arising out of or in connection with application of the products described herein except for that directly attributable to mechanisms and workmanship thereof. No license, express or implied, is granted under any patent, copyright or other intellectual property right of NEC.

Some electronic parts/components would fail or malfunction at a certain rate. In spite of every effort to enhance reliability of products by NEC, the possibility of failures and malfunction might not be avoided entirely. To prevent the risks of damage to death, human bodily injury or other property arising out thereof or in connection therewith, each customer is required to take sufficient measures in its safety designs and plans including, but not limited to, redundant system, fire-containment and anti-failure.

The products are classified into three quality grades: "**Standard**", "**Special**", and "**Specific**" of the highest grade of a quality assurance program at the choice of a customer. Each quality grade is designed for applications described below. Any customer who intends to use a product for application other than that of Standard quality grade is required to contact an NEC sales representative in advance.

The **Standard** quality grade applies to the products developed, designed and manufactured in accordance with the NEC standard quality assurance program, which are designed for such application as any failure or malfunction of the products (sets) or parts/components incorporated therein a customer uses are, directly or indirectly, free of any damage to death, human bodily injury or other property, like general electronic devices.

Examples: Computers, office automation equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment, industrial robots, etc.

The **Special** quality grade applies to the products developed, designed and manufactured in accordance with an NEC quality assurance program stricter than the standard one, which are designed for such application as any failure or malfunction of the products (sets) or parts/components incorporated therein a customer uses might directly cause any damage to death, human bodily injury or other property, or such application under more severe condition than that defined in the Standard quality grade without such direct damage.

Examples: Control systems for transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, medical equipment not specifically designed for life support, safety equipment, etc.

The **Specific** quality grade applies to the products developed, designed and manufactured in accordance with the standards or quality assurance program designated by a customer who requires an extremely higher level of reliability and quality for such products.

Examples: Military systems, aircraft control equipment, aerospace equipment, nuclear reactor control systems, medical equipment/devices/systems for life support, etc.

The quality grade of this product is the "**Standard**" unless otherwise specified in this document.

PRELIMINARY

CONTENTS

INTRODUCTION	2
1. OUTLINE.....	4
1.1 STRUCTURE AND PRINCIPLE.....	4
1.2 APPLICATION.....	4
1.3 FEATURES.....	4
2. GENERAL SPECIFICATIONS	5
3. BLOCK DIAGRAM.....	6
4. DETAILED SPECIFICATIONS	7
4.1 MECHANICAL SPECIFICATIONS.....	7
4.2 ABSOLUTE MAXIMUM RATINGS	7
4.3 ELECTRICAL CHARACTERISTICS	8
4.3.1 LCD panel signal processing board	8
4.3.2 Backlight lamp.....	9
4.3.3 Power supply voltage ripple.....	11
4.3.4 Fuse.....	11
4.4 POWER SUPPLY VOLTAGE SEQUENCE	12
4.5 CONNECTIONS AND FUNCTIONS FOR INTERFACE PINS.....	13
4.5.1 LCD panel signal processing board	13
4.5.2 Backlight lamp.....	14
4.5.3 Positions of plug and socket	15
4.6 SELECTION OF LVDS DATA INPUT MAP	16
4.6.1 Mode A	16
4.6.2 Mode B	17
4.7 DISPLAY COLORS AND INPUT DATA SIGNALS	18
4.8 DISPLAY POSITION.....	19
4.9 INPUT SIGNAL TIMINGS.....	19
4.9.1 Timing characteristics	19
4.9.2 Input signal timing chart	20
4.10 OPTICS.....	21
4.10.1 Optical characteristics.....	21
4.10.2 Definition of contrast ratio.....	22
4.10.3 Definition of luminance uniformity	22
4.10.4 Definition of response times	22
4.10.5 Definition of viewing angles.....	22
5. RELIABILITY TESTS.....	23
6. PRECAUTIONS	24
6.1 MEANING OF CAUTION SIGNS	24
6.2 CAUTIONS	24
6.3 ATTENTIONS	24
6.3.1 Handling of the product	24
6.3.2 Environment.....	25
6.3.3 Characteristics.....	26
6.3.4 Other	26
7. OUTLINE DRAWINGS	27
7.1 FRONT VIEW	27
7.2 REAR VIEW	28
REVISION HISTORY	29

1. OUTLINE

1.1 STRUCTURE AND PRINCIPLE

Color LCD module NL128102BC29-10 is composed of the amorphous silicon thin film transistor liquid crystal display (a-Si TFT LCD) panel structure with driver LSIs for driving the TFT (Thin Film Transistor) array and a backlight.

The a-Si TFT LCD panel structure is injected liquid crystal material into a narrow gap between the TFT array glass substrate and a monochrome-filter glass substrate.

Grayscale data signals from a host system (e.g. signal generator, etc.) are modulated into best form for active matrix system by a signal processing board, and sent to the driver LSIs which drive the individual TFT arrays.

The TFT array as an electro-optical switch regulates the amount of transmitted light from the backlight assembly, when it is controlled by data signals. Monochrome images are created by regulating the amount of transmitted light through the TFT array.

1.2 APPLICATION

- Monitor for PC


1.3 FEATURES

- Ultra-wide viewing angle (Adoption of Ultra-Advanced Super Fine TFT (UA-SFT))
- Wide color gamut
- High contrast
- LVDS interface
- Selectable LVDS data input map
- Edge light type (without inverter)

2. GENERAL SPECIFICATIONS

Display area	376.32 (H) × 301.056 (V) mm
Diagonal size of display	48cm (19.0 inches)
Drive system	a-Si TFT active matrix
Display color	16,777,216 colors
Pixel	1,280 (H) × 1,024 (V) pixels
Pixel arrangement	RGB (Red dot, Green dot, Blue dot) vertical stripe
Dot pitch	0.098 (H) × 0.294 (V) mm
Pixel pitch	0.294 (H) × 0.294 (V) mm
Module size	404.2 (W) × 330.0 (H) × 22.0 (D) mm (typ.)
Weight	(2,700) g (typ.)
Contrast ratio	(800:1) (typ.)
Viewing angle	At the contrast ratio ≥ 10:1 • Horizontal: Right side 88° (typ.), Left side 88° (typ.) • Vertical: Up side 88° (typ.), Down side 88° (typ.)
Designed viewing direction	Viewing angle with optimum grayscale ($\gamma=2.2$): normal axis (Perpendicular)
Polarizer surface	Antiglare
Polarizer pencil-hardness	3H (min.) [by JIS K5400]
Color gamut	At LCD panel center 72 % (typ.) [against NTSC color space]
Response time	$T_{on} + T_{off}$ (10% ← → 90%) (20) ms (typ.)
Luminance	At $IBL = 6.0 \text{ mA}_{rms} / \text{lamp}$ (300) cd/m^2 (typ.)
Signal system	LVDS 2 port (Receiver: THC63LVDF84B, THine Electronics Inc. or equivalent) [8bit digital signals for data of RGB colors, Dot clock (CLK), Data enable (DE)]
Power supply voltage	LCD panel signal processing board: 5.0V
Backlight	Edge light type: 6 cold cathode fluorescent lamps (without inverter)
Power consumption	At $IBL = 6.0 \text{ mA}_{rms} / \text{lamp}$, Checkered flag pattern TBD W (typ., Power dissipation of the inverter is not included.)

3. BLOCK DIAGRAM



Note1: Relations between GND (Signal ground), FG (Frame ground) and VBLC (Lamp low voltage terminal) in the LCD module are as follows.

GND - FG	Connected
GND - VBLC	Not connected
FG - VBLC	Not connected

Note2: GND and FG must be connected to customer equipment's ground, and it is recommended that GND, FG and customer inverter ground are connected together in customer equipment.

4. DETAILED SPECIFICATIONS

4.1 MECHANICAL SPECIFICATIONS

Parameter	Specification	Unit
Module size	404.2 ± 0.5 (W) $\times$ 330.0 ± 0.5 (H) $\times$ 22.0 ± 0.3 (D) Note1	Note2 mm
Display area	376.32 (H) $\times$ 301.056 (V)	Note2 mm
Weight	(2,700) (typ.), (2,850) (max.)	g

Note1: Excluding lamp cable, cable clamp and projections.

Note2: See "7. OUTLINE DRAWINGS".

4.2 ABSOLUTE MAXIMUM RATINGS

Parameter		Symbol	Rating	Unit	Remarks
Power supply voltage	LCD panel signal processing board	VDD	-0.3 to +6.0	V	Ta = 25°C
	Lamp voltage	VLH	2,000	Vrms	
Input voltage for signals	Display signals Note1	VD	-0.3 to +2.8	V	Ta = 25°C VDD= 5.0V
	Function signal Note2	VF		V	
Storage temperature		Tst	-20 to +60	°C	-
Operating temperature	Front surface	TopF	0 to +55	°C	Note3
	Rear surface	TopR	0 to +60	°C	Note4
Relative humidity Note5		RH	≤ 95	%	Ta $\leq 40^\circ\text{C}$
			≤ 85	%	$40 < \text{Ta} \leq 50^\circ\text{C}$
			≤ 70	%	$50 < \text{Ta} \leq 55^\circ\text{C}$
Absolute humidity Note5		AH	≤ 73 Note6	g/m ³	Ta $> 55^\circ\text{C}$
Operating altitude		-	$\leq 4,850$	m	$0^\circ\text{C} \leq \text{Ta} \leq 55^\circ\text{C}$
Storage altitude		-	$\leq 13,600$	m	$-20^\circ\text{C} \leq \text{Ta} \leq 60^\circ\text{C}$

Note1: Display signals are DA0+/-, DA1+/-, DA2+/-, DA3+/-, CKA+/-, DB0+/-, DB1+/-, DB2+/-, DB3+/-, CKB+/-

Note2: Function signal is TxSEL.

Note3: Measured at center of LCD panel surface (including self-heat)

Note4: Measured at center of LCD module's rear shield surface (including self-heat)

Note5: No condensation

Note6: Water amount at Ta = 55°C and RH = 70%

4.3 ELECTRICAL CHARACTERISTICS

4.3.1 LCD panel signal processing board

(Ta = 25°C)

Parameter		Symbol	min.	typ.	max.	Unit	Remarks
Power supply voltage		VDD	4.5	5.0	5.5	V	-
Power supply current		IDD	-	TBD Note1	TBD Note2	mA	at VDD = 5.0V
Permissible ripple voltage		VRP	-	-	100	mVp-p	for VDD
Differential input threshold voltage	High	VTH	-	-	+100	mV	at VCM = 1.2V Note3
	Low	VTL	-100	-	-	mV	
Terminating resistance		RT	-	100	-	Ω	-
Input voltage for TxSEL signal	High	VFH	Keep this pin open.			-	TxSEL Note4
	Low	VFL	-	-	0.5	V	
Input current for TxSEL signal		IFL	-80	-	-35	μA	

Note1: Checkered flag pattern [by EIAJ ED-2522]

Note2: Pattern for maximum current

Note3: Common mode voltage for LVDS receiver

Note4: TxSEL is pulled-up in the product. (Pull-up resistance: 50kΩ)

4.3.2 Backlight lamp


(Ta=25°C, Note1)

Parameter	Symbol	min.	typ.	max.	Unit	Remarks
Lamp current	IBL	3.5	6.0	7.0	mArms	at IBL=6.0mArms: (300) cd/m ² Note3
Lamp voltage	VBLH	-	650	-	Vrms	Note2, Note3
Lamp starting voltage	VS	1,350	-	-	Vrms	Ta = 25°C Note2, Note3, Note6
		1,550	-	-	Vrms	Ta = 0°C Note2, Note3, Note6
Lamp oscillation frequency	FO	40	48	55	kHz	Note4

Note1: This product consists of 6 backlight lamps, and these specifications are for each lamp.

Note2: The lamp voltage cycle between lamps should be kept on a same phase. "VS" and "VBLH" are the voltage value between low voltage side (Cold) and high voltage side (Hot).

Note3: The asymmetric ratio of working waveform for lamps (Power supply voltage peak ratio, power supply current peak ratio and waveform space ratio) should be less than 5 % (See the following figure.). If the waveform is asymmetric, DC (Direct current) element apply into the lamp. In this case, a lamp lifetime may be shortened, because a distribution of a lamp enclosure substance inclines toward one side between low voltage terminal (Cold terminal) and high voltage terminal (Hot terminal). When designing the inverter, evaluate asymmetric of lamp working waveform sufficiently.



Pa: Supply voltage/current peak for positive, Pb: Supply voltage/current peak for negative
Sa: Waveform space for positive part, Sb: Waveform space for negative part

Note4: In case "FO" is not the recommended value, beat noise may display on the screen, because of interference between "FO" and "1/th". Recommended value of "FO" is as following.

$$FO = \frac{1}{4} \times \frac{1}{th} \times (2n-1)$$

th: Horizontal cycle (See "4.9.1 Timing characteristics".)


n: Natural number (1, 2, 3)

Note5: Method of lamp cable installation may invite fluctuation of lamp current and voltage or asymmetric of lamp working waveform. When designing method of lamp cable installation, evaluate the fluctuation of lamp current, voltage and working waveform sufficiently.

Note6: In case of Inverter with Ballast condenser, "VS" is the voltage level between Ballast condenser and Connector (Refer to the below "Example of measurement"). "VS" should be designed to be more than minimum "VS". Otherwise the lamp may not be turned on because the lamp starting voltage is less than minimum "VS".

Example of measurement

Probe capacity: 3pF (Tektronix, inc.: P6015A)



4.3.3 Power supply voltage ripple

This product works, even if the ripple voltage levels are beyond the permissible values as following the table, but there might be noise on the display image.

Power supply voltage		Ripple voltage (Measure at input terminal of power supply)	Note1	Unit
VDD	5.0V	≤ 100		mVp-p

Note1: The permissible ripple voltage includes spike noise.


4.3.4 Fuse

Parameter	Fuse		Rating	Fusing current	Remarks
	Type	Supplier			
VDD	TBD	TBD	(2.5 A)	(6.25 A) 5min. max.	Note1
			(32 V)		

Note1: The power supply capacity should be more than the fusing current. If it is less than the fusing current, the fuse may not blow in a short time, and then nasty smell, smoke and so on may occur.

2

4.4 POWER SUPPLY VOLTAGE SEQUENCE



* These signals should be measured at the terminal of 100 Ω resistance.

Note1: In terms of voltage variation (voltage drop) while VDD rising edge is below 4.5V, a protection circuit may work, and then this product may not work.

Note2: Display signals (DA0+/-, DA1+/-, DA2+/-, DA3+/-, CKA+/-, DB0+/-, DB1+/-, DB2+/-, DB3+/-, CKB+/-) and TxSEL signal must be "0" voltage, exclude the VALID period (See above sequence diagram). If these signals are higher than 0.3V, the internal circuit is damaged. If some of display and function signals of this product are cut while this product is working, even if the signal input to it once again, it might not work normally. VDD should be cut when the display and function signals are stopped.

Note3: The backlight should be turned on within the valid period of display and function signals, in order to avoid unstable data display.

4.5 CONNECTIONS AND FUNCTIONS FOR INTERFACE PINS

4.5.1 LCD panel signal processing board

CN1 socket (LCD module side): FI-X30SSL-HF (Japan Aviation Electronics Industry Limited (JAE))
 Adaptable plug: FI-X30C series/ FI-X30H series/ FI-X30M series
 (Japan Aviation Electronics Industry Limited (JAE))

Pin No.	Symbol	Signal	Remarks
1	DA0-	Odd pixel data 0	Note1
2	DA0+		
3	DA1-	Odd pixel data 1	Note1
4	DA1+		
5	DA2-	Odd pixel data 2	Note1
6	DA2+		
7	GND	Ground	Note2
8	CKA-	Odd pixel clock	Note1
9	CKA+		
10	DA3-	Odd pixel data 3	Note1
11	DA3+		
12	DB0-	Even pixel data 0	Note1
13	DB0+		
14	GND	Ground	Note2
15	DB1-	Even pixel data 1	Note1
16	DB1+		
17	GND	Ground	Note2
18	DB2-	Even pixel data 2	Note1
19	DB2+		
20	CKB-	Even pixel clock	Note1
21	CKB+		
22	DB3-	Even pixel data 3	Note1
23	DB3+		
24	GND	Ground	Note2
25	TxSEL	Selection of LVDS data input map	Open: Mode A Low: Mode B Note3, Note4
26	RSVD	-	Keep this pin Open.
27	N.C.	-	Keep this pin Open.
28	VDD	Power supply	Note2
29			
30			

Note1: Twist pair wires with 100Ω (Characteristic impedance) should be used between LCD panel signal processing board and LVDS transmitter.

Note2: All GND and VDD terminals should be used without any non-connected lines.

Note3: TxSEL is pulled-up in the product. (Pull-up resistance: 50kΩ)

Note4: See "4.6 SELECTION OF LVDS DATA INPUT MAP".

PRELIMINARY

4.5.2 Backlight lamp

Attention: VBLH and VBLC must be connected correctly. Wrong connections will cause electric shock and also break down of the product.

CN201 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (Pink)
2	VBLC	Low voltage (Cold)	Cable color: (Gray)

2

CN202 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (White)
2	VBLC	Low voltage (Cold)	Cable color: (Gray)

2

CN203 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (Red)
2	VBLC	Low voltage (Cold)	Cable color: (Gray)

2

CN204 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (Pink)
2	VBLC	Low voltage (Cold)	Cable color:)Gray)

2

CN205 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (White)
2	VBLC	Low voltage (Cold)	Cable color: (Gray)


2

CN206 plug (LCD module side): BHSR-02VS-1 (J.S.T Mfg. Co., Ltd.)
Adaptable socket: SM02B-BHSS-1-TB(LF)(SN) (J.S.T Mfg. Co., Ltd.)
SM02B-BHSS-1-TB (J.S.T Mfg. Co., Ltd.)

Pin No.	Symbol	Signal	Remarks
1	VBLH	High voltage (Hot)	Cable color: (Red)
2	VBLC	Low voltage (Cold)	Cable color: (Gray)

2

4.5.3 Positions of plug and socket



4.6 SELECTION OF LVDS DATA INPUT MAP

4.6.1 Mode A

Input data		Note1	Transmitter			CN1	
			Pin	DS90CF383, C385 or equivalent		Pin	Symbol
Odd pixel data and control signal	RA0	→	51	TXIN0	Note2		
	RA1	→	52	TXIN1		1	DA0-
	RA2	→	54	TXIN2		2	DA0+
	RA3	→	55	TXIN3			
	RA4	→	56	TXIN4		3	DA1-
	RA5	→	3	TXIN6		4	DA1+
	GA0	→	4	TXIN7			
	GA1	→	6	TXIN8		5	DA2-
	GA2	→	7	TXIN9		6	DA2+
	GA3	→	11	TXIN12		7	GND
	GA4	→	12	TXIN13		8	CKA-
	GA5	→	14	TXIN14		9	CKA+
	BA0	→	15	TXIN15			
	BA1	→	19	TXIN18		10	DA3-
	BA2	→	20	TXIN19		11	DA3+
	BA3	→	22	TXIN20			
	BA4	→	23	TXIN21			
	BA5	→	24	TXIN22			
	Note3 RSVD	→	27	TXIN24			
	Note3 RSVD	→	28	TXIN25			
	DE	→	30	TXIN26			
	RA6	→	50	TXIN27			
	RA7	→	2	TXIN5			
	GA6	→	8	TXIN10			
	GA7	→	10	TXIN11			
	BA6	→	16	TXIN16			
	BA7	→	18	TXIN17			
	Note3 RSVD	→	25	TXIN23			
	CLK	→	31	CLKIN			
Even pixel data	RB0	→	51	TXIN0	Note2		
	RB1	→	52	TXIN1		12	DB0-
	RB2	→	54	TXIN2		13	DB0+
	RB3	→	55	TXIN3		14	GND
	RB4	→	56	TXIN4		15	DB1-
	RB5	→	3	TXIN6		16	DB1+
	GB0	→	4	TXIN7		17	GND
	GB1	→	6	TXIN8		18	DB2-
	GB2	→	7	TXIN9		19	DB2+
	GB3	→	11	TXIN12			
	GB4	→	12	TXIN13		20	CKB-
	GB5	→	14	TXIN14		21	CKB+
	BB0	→	15	TXIN15			
	BB1	→	19	TXIN18		22	DB3-
	BB2	→	20	TXIN19		23	DB3+
	BB3	→	22	TXIN20		24	GND
	BB4	→	23	TXIN21		25	TxSEL
	BB5	→	24	TXIN22		26	RSVD
	Note3 RSVD	→	27	TXIN24		27	N.C.
	Note3 RSVD	→	28	TXIN25		28	VDD
	Note3 RSVD	→	30	TXIN26		29	VDD
	RB6	→	50	TXIN27		30	VDD
	RB7	→	2	TXIN5			
	GB6	→	8	TXIN10			
	GB7	→	10	TXIN11			
	BB6	→	16	TXIN16			
	BB7	→	18	TXIN17			
	Note3 RSVD	→	25	TXIN23			
	CLK	→	31	CLKIN			

PRELIMINARY

NEC NEC LCD Technologies, Ltd.

NL128102BC29-10

4.6.2 Mode B

			Transmitter								
Input data		Note1	Pin	THC63LVDF83A/R or equivalent	Pin	THC63LVD823 or equivalent	CN1				
							Pin	Symbol			
Odd pixel data and control signal	RA2	→	51	TA0	53	R12	Note2				
	RA3	→	52	TA1	54	R13		1	DA0-		
	RA4	→	54	TA2	57	R14		2	DA0+		
	RA5	→	55	TA3	58	R15					
	RA6	→	56	TA4	59	R16					
	RA7	→	3	TA5	60	R17		TB1-	→	3	DA1-
	GA2	→	4	TA6	63	G12		TB1+	→	4	DA1+
	GA3	→	6	TB0	64	G13					
	GA4	→	7	TB1	65	G14		TC1-	→	5	DA2-
	GA5	→	11	TB2	66	G15		TC1+	→	6	DA2+
	GA6	→	12	TB3	67	G16				7	GND
	GA7	→	14	TB4	68	G17		TCLK1-	→	8	CKA-
	BA2	→	15	TB5	73	B12		TCLK1+	→	9	CKA+
	BA3	→	19	TB6	74	B13					
	BA4	→	20	TC0	75	B14		TD1-	→	10	DA3-
	BA5	→	22	TC1	76	B15		TD1+	→	11	DA3+
	BA6	→	23	TC2	77	B16					
	BA7	→	24	TC3	78	B17					
	Note3	RSVD	→	27	TC4	7		RSVD			
	Note3	RSVD	→	28	TC5	8		RSVD			
		DE	→	30	TC6	9		DE			
		RA0	→	50	TD0	51		R10			
		RA1	→	2	TD1	52		R11			
		GA0	→	8	TD2	61		G10			
		GA1	→	10	TD3	62		G11			
		BA0	→	16	TD4	69		B10			
		BA1	→	18	TD5	70		B11			
	Note3	RSVD	→	25	TD6	-					
		CLK	→	31	CLKIN	10		CLK			
	Even pixel data	RB2	→	51	TA0	81		R22	Note2		
		RB3	→	52	TA1	82		R23			
RB4		→	54	TA2	83	R24	TA2-	→		12	DB0-
RB5		→	55	TA3	84	R25	TA2+	→		13	DB0+
RB6		→	56	TA4	85	R26				14	GND
RB7		→	3	TA5	86	R27	TB2-	→		15	DB1-
GB2		→	4	TA6	91	G22	TB2+	→		16	DB1+
GB3		→	6	TB0	92	G23				17	GND
GB4		→	7	TB1	93	G24	TC2-	→		18	DB2-
GB5		→	11	TB2	94	G25	TC2+	→		19	DB2+
GB6		→	12	TB3	95	G26					
GB7		→	14	TB4	96	G27	TCLK2-	→		20	CKB-
BB2		→	15	TB5	99	B22	TCLK2+	→		21	CKB+
BB3		→	19	TB6	100	B23					
BB4		→	20	TC0	1	B24	TD2-	→		22	DB3-
BB5		→	22	TC1	2	B25	TD2+	→		23	DB3+
BB6		→	23	TC2	5	B26				24	GND
BB7		→	24	TC3	6	B27				25	TxSEL
Note3		RSVD	→	27	TC4	-				26	RSVD
Note3		RSVD	→	28	TC5	-				27	N.C.
Note3		RSVD	→	30	TC6	-				28	VDD
		RB0	→	50	TD0	79	R20			29	VDD
		RB1	→	2	TD1	80	R21			30	VDD
		GB0	→	8	TD2	89	G20				
		GB1	→	10	TD3	90	G21				
		BB0	→	16	TD4	97	B20				
		BB1	→	18	TD5	98	B21				
Note3		RSVD	→	25	TD6	-					
		CLK	→	31	CLKIN	-					

Note1: LSB (Least Significant Bit) – RA0, GA0, BA0, RB0, GB0, BB0

MSB (Most Significant Bit) – RA7, GA7, BA7, RB7, GB7, BB7

Note2: Twist pair wires with 100Ω (Characteristic impedance) should be used between LCD panel signal processing board and LVDS transmitter.


Note3: Input signal RSVD is not used inside the product, but do not keep pin open to avoid noise problem.

4.7 DISPLAY COLORS AND INPUT DATA SIGNALS

This product can display in equivalent to 16,777,216 colors in 256 gray scales. Also the relation between display colors and input data signals is as the following table.

Display colors		Data signal (0: Low level, 1: High level)																							
		RA7	RA6	RA5	RA4	RA3	RA2	RA1	RA0	GA7	GA6	GA5	GA4	GA3	GA2	GA1	GA0	BA7	BA6	BA5	BA4	BA3	BA2	BA1	BA0
		RB7	RB6	RB5	RB4	RB3	RB2	RB1	RB0	GB7	GB6	GB5	GB4	GB3	GB2	GB1	GB0	BB7	BB6	BB5	BB4	BB3	BB2	BB1	BB0
Basic Colors	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Red	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Magenta	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Green	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	Cyan	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
Red gray scale	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
		0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	dark	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	↑					:								:							:				
	↓					:								:							:				
	bright	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Green gray scale	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0
	dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0
	↑					:								:							:				
	↓					:								:							:				
	bright	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0
Blue gray scale	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
	dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0
	↑					:								:							:				
	↓					:								:							:				
	bright	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1
Blue		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0
	Blue	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1

4.8 DISPLAY POSITION



4.9 INPUT SIGNAL TIMINGS

4.9.1 Timing characteristics

Parameter			Symbol	min.	typ.	max.	Unit	Remarks
CLK	Frequency		1/tc	49	54	59	MHz	18.52 ns (typ.)
	Duty		-	-			-	Note2
	Rise time, Fall time		-				ns	
DATA	CLK-DATA	Setup time	-	-			ns	Note2
		Hold time	-				ns	
	Rise time, Fall time		-				ns	
DE	Horizontal	Cycl	th	12.3	15.63	20.59	μs	64.0 kHz (typ.) Note1, Note2
		Display period	thd	660	844	1,024	CLK	
	Vertical (One frame)	Cycle	tv	13.1	16.6	17.5	ms	60.0 Hz (typ.) Note1
		Display period	tvd	1,030	1,066	1,422	H	
	CLK-DE	Setup time	-	-			H	Note2
		Hold time	-				ns	
	Rise time, Fall time		-				ns	


Note1: Definition of parameters is as follows.

tc = 1CLK, th = 1H


Note2: See the data sheet of LVDS transmitter.

4.9.2 Input signal timing chart

Horizontal timing



Vertical timing



Note1: DATA (A) = RA0-RA7, GA0-GA7, BA0-BA7
DATA (B) = RB0-RB7, GB0-GB7, BB0-BB7

4.10 OPTICS

4.10.1 Optical characteristics

(Note1, Note2)


Parameter		Condition	Symbol	min.	typ.	max.	Unit	Measuring instrument	Remarks
Luminance		White at center $\theta R = 0^\circ, \theta L = 0^\circ, \theta U = 0^\circ, \theta D = 0^\circ$	L	(240)	(300)	-	cd/m ²	BM5A or SR-3	-
Contrast ratio		White/Black at center $\theta R = 0^\circ, \theta L = 0^\circ, \theta U = 0^\circ, \theta D = 0^\circ$	CR	TBD	(800)	-	-	BM5A or SR-3	Note3
Luminance uniformity		White $\theta R = 0^\circ, \theta L = 0^\circ, \theta U = 0^\circ, \theta D = 0^\circ$	LU	-	1.1	1.25	-	BM-5A	Note4
Chromaticity	White	x coordinate	Wx	-	0.313	-	-	SR-3	Note5
		y coordinate	Wy	-	0.329	-	-		
	Red	x coordinate	Rx	-	0.65	-	-		
		y coordinate	Ry	-	0.33	-	-		
	Green	x coordinate	Gx	-	0.29	-	-		
		y coordinate	Gy	-	0.62	-	-		
	Blue	x coordinate	Bx	-	0.14	-	-		
		y coordinate	By	-	0.08	-	-		
Color gamut		$\theta R = 0^\circ, \theta L = 0^\circ, \theta U = 0^\circ, \theta D = 0^\circ$ at center, against NTSC color space	C	65	72	-	%		
Response time		Black to white	Ton	-	(10)	(20)	ms	BM-5A	Note6 Note7
		White to black	Toff	-	(10)	(20)	ms		
Viewing angle	Right	$\theta U = 0^\circ, \theta D = 0^\circ, CR \geq 10$	θR	70	88	-	°	BM-5A, EZ Contrast	Note8
	Left	$\theta U = 0^\circ, \theta D = 0^\circ, CR \geq 10$	θL	70	88	-	°		
	Up	$\theta R = 0^\circ, \theta L = 0^\circ, CR \geq 10$	θU	70	88	-	°		
	Down	$\theta R = 0^\circ, \theta L = 0^\circ, CR \geq 10$	θD	70	88	-	°		

Note1: These are initial characteristics.

Note2: Measurement conditions are as follows.

Ta = 25°C, VDD = 5.0V, IBL = 6.0mA rms/lamp, Display mode: SXGA,
Horizontal cycle = 1/64.0kHz, Vertical cycle = 1/60.0Hz

Optical characteristics are measured after 20minutes from working the product, in the dark room. Also measurement methods are as follows.



Note3: See "4.10.2 Definition of contrast ratio".

Note4: See "4.10.3 Definition of luminance uniformity".

Note5: These coordinates are found on CIE 1931 chromaticity diagram.

Note6: Product surface temperature: TopF = (35)°C

Note7: See "4.10.4 Definition of response times".

Note8: See "4.10.5 Definition of viewing angles".

4.10.2 Definition of contrast ratio

The contrast ratio is calculated by using the following formula.


$$\text{Contrast ratio (CR)} = \frac{\text{Luminance of white screen}}{\text{Luminance of black screen}}$$

4.10.3 Definition of luminance uniformity

The luminance uniformity is calculated by using following formula.


$$\text{Luminance uniformity (LU)} = \frac{\text{Maximum luminance from ① to ⑤}}{\text{Minimum luminance from ① to ⑤}}$$

The luminance is measured at near the 5 points shown below.




4.10.4 Definition of response times

Response time is measured, the luminance changes from "black" to "white", or "white" to "black" on the same screen point, by photo-detector. Ton is the time it takes the luminance change from 10% up to 90%. Also Toff is the time it takes the luminance change from 90% down to 10% (See the following diagram.).



4.10.5 Definition of viewing angles




5. RELIABILITY TESTS

Test item		Condition	Judgment	Note1
High temperature and humidity (Operation)		① $60 \pm 2^{\circ}\text{C}$, RH = 60%, 240hours ② Display data is white.	No display malfunctions	
Heat cycle (Operation)		① $0 \pm 3^{\circ}\text{C}$...1hour $55 \pm 3^{\circ}\text{C}$...1hour ② 50cycles, 4hours/cycle ③ Display data is white.		
Thermal shock (Non operation)		① $-20 \pm 3^{\circ}\text{C}$...30minutes $60 \pm 3^{\circ}\text{C}$...30minutes ② 100cycles, 1hour/cycle ③ Temperature transition time is within 5 minutes.		
Vibration (Non operation)		① 5 to 100Hz, 11.76m/s^2 ② 1 minute/cycle ③ X, Y, Z directions ④ 10 times each directions	No display malfunctions No physical damages	
Mechanical shock (Non operation)		① 294m/s^2 , 11ms ② X, Y, Z directions ③ 3 times each directions		
ESD (Operation)		① 150pF, 150Ω , $\pm 10\text{kV}$ ② 9 places on a panel surface Note2 ③ 10 times each places at 1 sec interval	No display malfunctions	
Dust (Operation)		① Sample dust: No.15 (by JIS-Z8901) ② 15 seconds stir ③ 8 times repeat at 1 hour interval		
Low pressure	Operation	① 53.3 kPa ② $0^{\circ}\text{C} \pm 3^{\circ}\text{C}$...24 hours ③ $55^{\circ}\text{C} \pm 3^{\circ}\text{C}$...24 hours		
	Non-operation	① 15 kPa ② $-20^{\circ}\text{C} \pm 3^{\circ}\text{C}$...24 hours ③ $60^{\circ}\text{C} \pm 3^{\circ}\text{C}$...24 hours		

Note1: Display functions are checked under the same conditions as product inspection.

Note2: See the following figure for discharge points



6. PRECAUTIONS

6.1 MEANING OF CAUTION SIGNS

The following caution signs have very important meaning. **Be sure to read "6.2 CAUTIONS" and "6.3 ATTENTIONS", after understanding these contents!**



This sign has the meaning that customer will be injured by himself or the product will sustain a damage, if customer has wrong operations.



This sign has the meaning that customer will get an electrical shock, if customer has wrong operations.



This sign has the meaning that customer will be injured by himself, if customer has wrong operations.

6.2 CAUTIONS



*** Do not touch the working backlight. There is a danger of an electric shock.**



*** Do not touch the working backlight. There is a danger of burn injury.**
*** Do not shock and press the LCD panel and the backlight! There is a danger of breaking, because they are made of glass. (Shock: To be not greater 294m/s^2 and to be not greater 11ms, Pressure: To be not greater 19.6N ($\phi 16\text{mm}$ jig))**


6.3 ATTENTIONS



6.3.1 Handling of the product

- ① Take hold of both ends without touching the circuit board when the product (LCD module) is picked up from inner packing box to avoid broken down or misadjustment, because of stress to mounting parts on the circuit board.
- ② Do not hook nor pull cables such as lamp cable, and so on, in order to avoid any damage.
- ③ When the product is put on the table temporarily, display surface must be placed downward.
- ④ When handling the product, take the measures of electrostatic discharge with such as earth band, ionic shower and so on, because the product may be damaged by electrostatic.
- ⑤ The torque for product mounting screws must never exceed $0.67\text{N}\cdot\text{m}$. Higher torque might result in distortion of the bezel. And the length of product mounting screws from surface of plate(product side) must be 4.0mm to 7.0mm.

- ⑥ The product must be installed using mounting holes without undue stress such as bends or twist (See outline drawings). And do not add undue stress to any portion (such as bezel flat area). Bends or twist described above and undue stress to any portion may cause display mura.
Recommended installing method: Ideal plane "A" is defined by one mounting hole (datum point) and other mounting holes. The ideal plane "A" should be the same plane within $\pm$ TBD mm.



- ⑦ Do not press or rub on the sensitive product surface. When cleaning the product surface, use of the cloth with ethanolic liquid such as screen cleaner for LCD is recommended.
- ⑧ Do not push nor pull the interface connectors while the product is working.
- ⑨ Do not locate the lamp cable on the signal processing board. A noise may occur on the display image.
- ⑩ Properly connect the plug (backlight side) to adaptable socket (inverter side) without incomplete connection. After connecting, be careful not to hook the lamp cables because incomplete connection may occur by hooking the lamp cables. This incomplete connection may cause abnormal operation of high voltage circuit.
- ⑪ If the lamp cable is attached on the metal part of the product directly, high frequency leak current to the metal part may occur, then the brightness may decrease or the lamp may not be turned on.
- ⑫ When handling the product, use of an original protection sheet on the product surface (polarizer) is recommended for protection of product surface. Adhesive type protection sheet may change color or characteristics of the polarizer.
- ⑬ Usually liquid crystals don't leak through the breakage of glasses because of the surface tension of thin layer and the construction of LCD panel. But, if you contact with liquid crystal for the worst, please wash it out with soap.

2

6.3.2 Environment

- ① Do not operate or store in high temperature, high humidity, dewdrop atmosphere or corrosive gases. Keep the product in packing box with antistatic pouch in room temperature to avoid dusts and sunlight, when storing the product.
- ② In order to prevent dew condensation occurring by temperature difference, the product packing box should be opened after enough time being left under the environment of an unpacking room. Evaluate the leaving time sufficiently because a situation of dew condensation occurring is changed by the environmental temperature and humidity. (Recommended leaving time: 6 hours or more with packing state)
- ③ Do not operate in high magnetic field. Circuit boards may be broken down by it.
- ④ This product is not designed as radiation hardened.

6.3.3 Characteristics


The following items are neither defects nor failures.

- ① Response time, luminance and color may be changed by ambient temperature.
- ② Display mura, flicker, vertical seam or small spot may be observed depending on display patterns.
- ③ Optical characteristics (e.g. luminance, display uniformity, etc.) gradually is going to change depending on operating time, and especially low temperature, because the LCD has cold cathode fluorescent lamps.
- ④ Do not display the fixed pattern for a long time because it may cause image sticking. Use a screen saver, if the fixed pattern is displayed on the screen.
- ⑤ The display color may be changed depending on viewing angle because of the use of condenser sheet in the backlight.
- ⑥ Optical characteristics may be changed depending on input signal timings.
- ⑦ The interference noise between input signal frequency for this product's signal processing board and luminance control frequency of the inverter may appear on a display. Set up luminance control frequency of the inverter so that the interference noise does not appear.
- ⑧ After the product is stored under condition of low temperature or dark place for a long time, the cold cathode fluorescent lamp may not be turned on under the same condition because of the general characteristic of cold cathode fluorescent lamp. In addition, when Luminance control ratio is low in pulse width modulation method inverter, the lamp may not be turned on. In this case, power should be supplied again.

6.3.4 Other

- ① All GND and VDD terminals should be used without any non-connected lines.
- ② Do not disassemble a product or adjust variable resistors.
- ③ Pack the product with original shipping package, in order to avoid any damages during transportation, when returning the product to NEC for repair and so on.
- ④ The LCD module by itself or integrated into end product should be packed and transported with display in the vertical position. Otherwise the display characteristics may be degraded.


7. OUTLINE DRAWINGS
7.1 FRONT VIEW



Note1: The torque for product mounting screws must never exceed 0.67N·m. And the length of product mounting screws from surface of plate(product side) must be 4.0mm to 7.0mm.
Note2: Excluding lamp cable, cable clamp and projections.
Note3: The values in parentheses are for reference.

Unit: mm

7.2 REAR VIEW



Note1: The values in parentheses are for reference.
Note2: The cable of up side and down side is the same length.

Unit: mm

PRELIMINARY

REVISION HISTORY

The inside of latest specifications is revised to the clerical error and the major improvement of previous edition. Only a changed part such as functions, characteristic value and so on that may affect a design of customers, are described especially below.

Edition	Document number	Prepared date	Revision contents and signature
1st edition	DOD-PP-0486	Feb. 29, 2008	Revision contents New issue Writer <i>Approved by</i> _____ <i>Checked by</i> _____ <i>Prepared by</i> _____ T. OGAWA _____ E. KATAYAMA _____
2nd edition	DOD-PP-0492	Mar. 10, 2008	Revision contents P5 General specifications • Restonse time: (16) ms(typ.) → (20) ms(typ.) P6 Block diagram • GND-FG: Not connected → Connected P9 Electrical characteristics - Backlight lamp • Lamp current: 300cd/m ² → (300)cd/m ² (correction) P11 Fuse • Rating: (4.0A), (25V) → (2.5A), (32V) • Fusing current: (8.0A), 1min. max. → (6.25A), 5min. max. P14 Backlight lamp - CN201, CN202, CN203, CN204, CN205, CN206 • Low voltage: Cable color: (White) → Cable color: (Gray) P21 Optical characteristics - Response time • Black to white, White to black: (8) ms(typ.), (16) ms(max.) → (10) ms(typ.), (20) ms(max.) P24-25 Attentions - Handling the product • ⑤ (change of expression) • ⑫ (elmination) P27 Outline drawings • Depth: 4.0 to 7.0 → Note1 (change) Signature of writer <i>Approved by</i> _____ <i>Checked by</i> _____ <i>Prepared by</i> _____  _____  _____ T. OGAWA _____ E. KATAYAMA _____